


Arrangements Broken Line

Designed by Michael Anastassiades, 2018



29W - 1200lm - 2700K

Diffuse light suspended lighting device. Body in extruded, curved NC-machined and black powder-coated aluminium, diffuser in platinum optical silicone. Each component can be connected to the power pack by means of an electrical and mechanical connection system designed for customisable product set-up. Roses available with two powers: lamp with power under 70W and lamp with power under 190W. Class III roses also available for installations with remote power supply: "surface" version for installations on cement, "recessed" version for plasterboard ceilings. The electronics integrated in the rose enables use of dimming systems: push, 1-10, potentiometer, DALI. In the absence of these systems, the light flow can be set with the push system included in the rose. Cable length 2.4m



Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT

Main specifications

EAN	8059607014097
Mounting	Suspension
Enviroment	Indoor dry location
Light source type	LED
LED type	LED Module
Lamp holder	LED Module
Power (W)	29
System flux (lm)	1200

Physical

Colour	Black
Cord length (mm)	2500
Net weight (kg)	0.5
Package height (cm)	5
Package width (cm)	81
Package length (cm)	78
Package volume (m3)	0.03
IP	20

Download

Mounting instructions	↓ PDF
Spare Parts	↓ PDF

Photometric Files


LDT / IES	↓ LDT
-----------	-------

Technical Drawings

2D	↓ ZIP
3D	↓ ZIP




Schematic light drawing



Ecodesign and Energy
Labelling

This product contains a light
source of energy efficiency
class F



Replaceable (LED only)
light source by a
professional


Photometric

Lighting type	Indirect, Direct
Light distribution	Symmetric
CCT (K)	2700

Electrical

Insulation class	III
Frequency (Hz)	50/60
Main voltage (Vac)	48
Driver	Remote
Dimmable	Yes
Dimming interface	Remote Dimmable (Dimmer Not Included)
Batteries inside	No
Charging min time	No


Accessories & Power Supply



REQUIRED

F0415030


Arrangements Big Rose



REQUIRED

F0416030

Arrangements Small Rose



REQUIRED

F0418030

Arrangements Recessed Rose